

INSTALLATION

Prerequisites

The following hardware and system software is needed to execute Credit Card/400. Please ensure that all needed system software is installed before beginning the installation.

AS/400:

- + OS/400 Version 4, Release 2, Modification 0 or greater with:
 - TCP/IP Connectivity Utilities (57xx-TC1)
 - IBM HTTP Server for AS/400 (57xx-DG1)
 - Digital Certificate Manager (Product Option 34)
 - Cryptographic Access Provider for AS/400 (57xx-AC3)

Installation

- 1) Sign on as **QSECOFR**

WARNING:

The instructions below are for loading Credit Card/400 onto your system for the first time. If you are updating your existing Credit Card/400 to a new release, refer to the document “**Credit Card/400 Update Instructions**”.

- 2) Restore the install routines from the media.

Mount the media and enter one of the following:

If you are using Tape:

```
RSTOBJ OBJ(BCCIN*) SAVLIB(CCRD40) DEV(xxxxxx) VOL(*MOUNTED)  
RSTLIB(QTEMP)
```

If you are using CD-ROM:

```
RSTOBJ OBJ(BCCIN*) SAVLIB(CCRD40) DEV(OPT01) VOL(BDS)  
RSTLIB(QTEMP) OPTFILE(CCRD40)
```

If you are using a Save file:

```
RSTOBJ OBJ(BCCIN*) SAVLIB(CCRD40) DEV(*SAVF) SAVF(IIII/ffff)  
RSTLIB(QTEMP)
```

Enter the lib/name of the save file containing library **CCRD40**.

Press **ENTER**

CREDIT CARD/400™

- 3) Execute the install procedure. Enter one of the following:

If you are using Tape or CD-ROM:

QTEMP/BCCINS DEV(XXXXX)

If you are using a Save file:

QTEMP/BCCINS DEV(*SAVF) PGMSAVF(aaaaa) DTASAVF(bbbbb)

Enter the save file containing library **CCRD40** for aaaaa. Enter the save file containing library **CCRD40DATA** for bbbb..

You will receive the message “Installation of Credit Card/400 complete”. You may need to call Broderick Data Systems to activate your 30-day trial package. You will first need to add library **BRODERICK** to your library list.

- 4) Access the BDS Software Server (optional).

Note: Your AS/400 must be connected to the Internet to perform this procedure.

- a) If you have not done so previously, access the tailoring options screen:

BRODERICK/BCCSETUP

b) Note the fields “BDS Access Userid” and “Password”. You will need a user ID and password to access some of the server options. If needed, contact BDS administration to get this information. If you add your user id and password, press **ENTER** to enter them and re-enter the setup command.

c) Press F14, E-Comm. The Software Server display will appear. Take note of the options available to you. When you are finished, press F3 to exit

Continue with Chapter 3, “**Planning Guide**”.