

# INSTALLATION

## *Prerequisites*

The following hardware and system software is needed to execute Spool PDF Overlay/400. Please ensure that all needed system software is installed before beginning the installation.

### **AS/400:**

- + OS/400 Version 5, Release 4, Modification 0 or greater
- + Security level 40 or less

### **Retrieve Font Attributes Utility:**

To retrieve Font Attributes in existing PDF files:

- + Windows 2000, Windows XP, Windows 7, or Windows Server 2003
- + DotNet Framework 2.0 or greater

## *Installation*

- 1) Sign on as **QSECOFR**

### **WARNING:**

The instructions below are for loading Spool PDF Overlay/400 onto your system for the first time. If you are updating your existing Spool PDF Overlay/400 software to a new release, refer to the document “**Spool PDF Overlay/400 Update Instructions**”.

- 2) Restore the install routines from the media.

Mount the media and enter one of the following:

If you are using Tape:

```
RSTOBJ OBJ(BOVIN*) SAVLIB(SPDF40) DEV(xxxxxx) VOL(*MOUNTED)
RSTLIB(QTEMP)
```

If you are using CD-ROM:

```
RSTOBJ OBJ(BOVIN*) SAVLIB(SPDF40) DEV(OPT01) VOL(BDS)
RSTLIB(QTEMP) OPTFILE(SPDF40)
```

If you are using a Save file:

```
RSTOBJ OBJ(BOVIN*) SAVLIB(SPDF40) DEV(*SAVF) SAVF(IIII/ffff)
RSTLIB(QTEMP)
```

Enter the lib/name of the save file containing library **SPDF40**.

# SPOOL PDF OVERLAY/400™

Press **ENTER**

3) Execute the install procedure. Enter one of the following:

If you are using Tape or CD-ROM:

**QTEMP/BOVINS DEV(xxxxx)**

If you are using a Save file:

**QTEMP/BOVINS DEV(\*SAVF) PGMSAVF(aaaaa) DTASAVF(bbbbb)**

Enter the save file containing library **SPDF40** for aaaaa. Enter the save file containing library **SPDF40DATA** for bbbbb.

Press **ENTER**.

You will receive the message “Installation of Spool PDF Overlay/400 complete”. You may need to call Broderick Data Systems to activate your 30 day trial package. You will first need to add library **BRODERICK** to your library list.

4) Access the BDS Software Server (optional).

**Note:** Your AS/400 must be connected to the Internet to perform this procedure.

a) If you have not done so previously, access the tailoring options screen:

**BRODERICK/BOVSETUP**

b) Note the fields “BDS Access Userid” and “Password”. You will need a user ID and password to access some of the server options. If needed, contact BDS administration to get this information. If you add your user id and password, press **ENTER** to enter them and re-enter the setup command.

c) Press F14, E-Comm. The Software Server display will appear. Take note of the options available to you. When you are finished, press F3 to exit