

DEFINE TAILORING OPTIONS

This allows the Administrator to define system wide options. To access the Tailoring Options screen, select option 1 from the Menu or enter the following command:

BRODERICK/BOVSETUP

The following screen will appear:

```
Spool PDF Overlay/400 (TM)      11/7/09 10:41:07
Setup Display                      Prc  LPAR
System Statistics: Rel Mod PTF  System Name  CPU Serial  Model Grp  Num
                   01  02 0000  BDS400      00000000    E4A  P05 00001
Passwords: Permanent              Temporary  High Avial
                   F1F2F3F4F5F6F7F8  FAFBFCFDFEFF  F1F2F3F4F5F6F7F8

EBCDIC CCSID:    ___ 37
ASCII CCSID:     ___ 437

BDS Access Userid: _____ Password: _____

F3=Exit w/o Update F12=Exit w/o Update F14=BDS SwSvr
Copyright 2009, 2013 Broderick Data Systems
```

The above parameters have the following definitions:

System Statistics

Rel, Mod and PTF

This is the Release, Modification and Program Temporary Fix level of Spool PDF Overlay/400 you have installed.

Note: When the update to Spool PDF Overlay/400 is done, it will update these fields. If you update Spool PDF Overlay/400 and these fields do not update, verify you have executed the update procedure in the Spool PDF Overlay/400 Update Instructions.

System Name

The system name assigned to the iSeries computer running the Spool PDF Overlay/400 software.

CPU Serial Number

The CPU serial number assigned to this iSeries computer.

SPOOL PDF OVERLAY/400™

Model

The model number of this iSeries computer.

Proc Grp (Processor Group)

The Processor Group of this iSeries computer. The Processor Group is a designation designed by IBM to group its hardware for tiered pricing purposes. BDS also uses IBM's groupings for pricing purposes.

Passwords

Permanent and Temporary Passwords

Passwords are provided by Broderick Data Systems to allow access to Spool PDF Overlay/400. Certain key functions test these passwords before executing. If the password tests fail, a message will appear on the **QSYSOPR** message queue and the function stops.

High Availability Password

If this machine is being replicated to a High Availability machine, specify the Permanent Password for the HA machine here. This will allow you to cut over to the HA machine without changing passwords. Note: You must purchase an HA license from Broderick Data Systems in order to receive an HA password.

BDS Access User ID and Password

Specifies the user ID and password needed to access the BDS Software Server. Contact BDS Administration for your user ID and password.

Other Options

EBCDIC and ASCII CCSID

Specifies the EBCDIC to ASCII conversion scheme to use. Please note that the iSeries is an EBCDIC machine and PDF is an ASCII specification. Spool PDF Overlay/400 will convert data from the specified EBCDIC character set ID to the specified ASCII character set ID. For more information refer to AS/400 National Language Support, Appendix G.2 "Code Pages and CCSID's"

Notes:

- 1) Specified CCSID's will be checked by issuing a test string to convert. Errors will be reported back to the user. For a list of errors and their meanings refer to "OS/400 National Language API's", Chapter 3.2.2 "CDRCVRT API Feedback Codes and Conditions". No error message does not insure a proper conversion. We recommend you test the conversion by creating a PDF and displaying it in Adobe Acrobat.
- 2) CCSIDs 37 and 437 are US English EBCDIC and ASCII.

DEFINE TAILORING OPTIONS

F3 (Return)

Press F3 to exit without updating.

Access the BDS Software Server

If **F14** is chosen, the screen showing BDS Software Server options is displayed. To access the BDS Software Server the AS/400 must be connected to the Internet. The following display will appear:

```

12/03/01      11:45:21
BDS Software Server Display

Select one of the following:

1. Check for updates
2. Download Software Update
3. Download Software Patch
4. Upload Captured Problem Data

Option:

F3=Exit  F12=Exit
```

Some of the following options require a user ID and password. If you do not have one, contact BDS Administration. These options use the Internet to connect to a server at Broderick Data Systems. Therefore your AS/400 must be connected to the Internet. If behind a firewall, the firewall must allow outbound sessions through it.

Check for updates

Retrieves the latest available release of the product. Displays the BDS and OS/400 prerequisite releases required to install the latest release of the product.

Download Software Update

Downloads the latest release of the product into save files on your system. The update procedure can then be done using these save files. The product may be active and running while you perform this download.

Download Software Patch

Downloads objects into a save file on your system. Usually you will use this option while working with BDS tech support.

SPOOL PDF OVERLAY/400™

Upload Captured Problem Data

Uploads a save file on your system (containing objects that you have saved) into a save file on the BDS server. Usually you will use this option while working with BDS tech support.

F3 (Return)

Press F3 to exit.

F12 (Return)

Press F12 to exit.